

Be sure, be safe.

COSMOS

PORTABLE SEMICONDUCTOR GAS DETECTOR

XPS-7II

World's Smallest Portable Gas Detector for NF₃ Detection

Various semiconductor gases can be detected
by changing the sensor unit



• CE marking

Features

- **NF₃ can be detected without any optional equipment.**
- **The calibrated gas sensor unit can be replaced on site, reducing maintenance work.**
- **Large LCD**
- **2-way power supply: Dry batteries and AC power supply (optional)**
- **Small and lightweight**
- **The speed of alarm sound changes depending on gas concentration.**

Detectable Gas List

Sensor unit model	Detectable gas		F.S.	Alarm set value	
				1st stage	2nd stage
XDS-7NH	NH ₃	Ammonia	100ppm	12ppm	25ppm
XDS-7SH	SiH ₄	Silane	25ppm	2.5ppm	5ppm
XDS-7DC	SiH ₂ Cl ₂	Dichlorosilane	25ppm	2.5ppm	5ppm
XDS-7AH	AsH ₃	Arsine	250ppb	25ppb	50ppb
XDS-7PH	PH ₃	Phosphine	1ppm	0.15ppm	0.3ppm
XDS-7BH	B ₂ H ₆	Diborane	500ppb	50ppb	100ppb
XDS-7SE	H ₂ Se	Hydrogen selenide	250ppb	25ppb	50ppb
XDS7GH	GeH ₄	Germane	1ppm	0.1ppm	0.2ppm
XDS-7CL	Cl ₂	Chlorine	5ppm	0.25ppm	0.5ppm
XDS-7CF	ClF ₃	Chlorine trifluoride	1ppm	0.05ppm	0.1ppm
XDS-7HC	HCl	Hydrogen chloride	25ppm	2.5ppm	5ppm
XDS-7HF	HF	Hydrogen fluoride	10ppm	1.5ppm	3ppm
XDS-7HB	HBr	Hydrogen bromide	10ppm	1.5ppm	3ppm
XDS-7NO	NO	Nitrogen monoxide	100ppm	12ppm	25ppm
XDS-7HS	H ₂ S	Hydrogen sulfide	50ppm	5ppm	10ppm
XDS-7CO	CO	Carbon monoxide	250ppm	12.5ppm	25ppm
XDS-7DS	Si ₂ H ₆	Disilane	25ppm	2.5ppm	5ppm
XDS-7F ₂	F ₂	Fluorine	5ppm	0.5ppm	1ppm
XDS-7O ₃	O ₃	Ozone	1ppm	0.05ppm	0.1ppm
XDS-7NF	NF ₃	Nitrogen trifluoride	100ppm	5ppm	10ppm

Specifications

Detection Principle	Electrochemical, Electrochemical + pyrolyzer
Target Gas	Semiconductor gases
Sampling Method	Extractive
Measuring Range	As per delivery specifications
Accuracy *1	±10%F.S. except for XDS-7NF -30%F.S. to +10%F.S. for XDS-7NF
Response time *1	T60: Less than 60 seconds
Display	Four-digit on LCD
Power Source	Alkaline AA battery x 4pcs or Dedicated 100-240VAC/6VDC adapter (optional)*3
Continuous Operating Time*2	More than 12 hours except for XDS-7NF More than 8 hours for XDS-7NF (by alkaline AA batteries (Toshiba LR6AN) at 20°C, with no gas alarm)
Operating Temperature and Humidity	0 to +40°C, 30 to 85%RH
Compliance	CE (EMC: 2014/30/EU) *3 *4
Dimensions	Approx. W62 × H150 × D128 mm (excluding protrusions)
Mass	Approx. 1.3 kg

*1. Under identical conditions.

*2. The operating time (battery life) may vary depending on environment and conditions of use, storage period, battery manufacturer etc.

*3. AC power adapter does not comply with CE marking.

*4. There are two types of EC-7 sensor stocker, global and domestic (for use in Japan). Global type is CE-marked.

Optional Accessory



- Sensor stocker (for six sensor units) [EC-7]



NEW COSMOS ELECTRIC CO., LTD.

Offices

Head Office (Osaka, Japan)

2-5-4 Mitsuyanaka, Yodogawa-ku, Osaka, Japan 5320036

Phone: +81-6-6885-8484

E-mail: e-info@new-cosmos.co.jp

Thailand Office

4345 Bhiraj Tower at BITEC, 23rd Floor, Sukhumvit Rd.,

South Bangna, Bangna, Bangkok 10260 Thailand

Phone: +66-2-017-5175

E-mail: info.cosmosthailand@new-cosmos.co.th

Paris Office

128 Rue Du Faubourg Saint-Honore, 75008 Paris, France

Phone: +33 6-62-93-51-53

E-mail: info@new-cosmos.fr

Group Companies

NEW COSMOS ELECTRIC (SHANGHAI) CO., LTD.

4th Plant No.385, Dongxing Road, Songjiang Industrial Zone,

Shanghai, China 201613

Phone: +86-21-6774-3138

E-mail: info@new-cosmos.com.cn

NEW COSMOS ELECTRIC KOREA CO., LTD.

3F,4F BMY Tower, 16, Teheran-ro 27-gil, Gangnam-gu, Seoul, Korea

Phone: +82-2-555-3102

E-mail: info@new-cosmos.co.kr

TAIWAN NEW COSMOS ELECTRIC CO.,LTD

10F-3, No. 93, Shuiyuan St., East Dist., Hsinchu City 300042, Taiwan

Phone: +886-3-574-4593

E-mail: cosmost1@ms75.hinet.net

New Cosmos USA, Inc.

650 Warrenville Road, Suite 101, Lisle, IL 60532, USA

Phone: +1-847-749-3064

E-mail: support@newcosmosusa.com

New Cosmos-BIE (Netherlands)

Maxwellstraat 7, NL-1704 SG, Heerhugowaard,

the Netherlands

Phone: +31-72-576-5630

E-mail: sales@newcosmos-europe.com



SAFETY WARNING

Carefully read the instruction manual prior to use.

Select and use the device designed to detect the required type of gas. Use of a wrong sensor type may cause an accident.